

Code No: 126VK

JAWAHARLAL NEHRU TECHNOLOGICAL UNIVERSITY HYDERABAD

B. Tech III Year II Semester Examinations, April - 2018

DIGITAL SIGNAL PROCESSING

(Common to ECE, EIE)

Time: 3 hours

Max. Marks: 75

Note: This question paper contains two parts A and B. Part A is compulsory which carries 25 marks. Answer all questions in Part A. Part B consists of 5 Units. Answer any one full question from each unit. Each question carries 10 marks and may have a, b, c as sub questions.

PART- A

(25 Marks)

- 1.a) Show that $\delta(n) = u(n) - u(n-1)$ [2]
- b) Find the Z-transform $f(n) = n^2 u(n)$ [3]
- c) State and prove the any three properties of DFT. [2]
- d) What is the basic operation of DIF algorithm? [3]
- e) What are the properties of Butterworth Low pass filter? [2]
- f) Discuss the stability of the impulse invariant mapping technique [3]
- g) Explain the effects of truncating an infinite Fourier series into a finite series. [2]
- h) What is the condition for the impulse response of FIR filter to satisfy for constant group and phase delay and for constant group delay? [3]
- i) What is the need for Multirate Digital Signal Processing [2]
- j) What do you mean by quantization step size? [3]

PART-B

(50 Marks)

2.a) An LTI system is characterized by an impulse response

$$h(n) = \left(\frac{3}{4}\right)^n u(n)$$

- b) Find the step response of the system. Also, evaluate the output of the system at $n=\pm 5$. [5+5]
- Consider a discrete-time system characterized by the following input-output relationship $y(n) = x(n - 2) - 2x(n - 17)$. Determine whether the system is memory less, time-Invariant, linear, causal and stable. [5+5]

OR

3.a) Given the difference equation $y(n) + b^2 y(n - 2) = 0$ for $n \geq 0$ and $|b| < 1$. With initial conditions $y(-1) = 0$ and $y(-2) = -1$, Show that

$$y(n) = b^{n+2} \cos\left(\frac{n\pi}{2}\right)$$

b) Find the Z-transform of the sequence $f(n)$ defined below:

[5+5]

$$f(n) = \begin{cases} 3^n & n < 0 \\ \left(\frac{1}{3}\right)^n & n = 0, 2, 4, \dots \\ \left(\frac{1}{2}\right)^n & n = 1, 3, 5, \dots \end{cases}$$

4.a) Find the IDFT of the sequence $X(K)$ given below

$$X(K) = \{1, 0, 0, j, 0, -j, 0, 0\}$$

b) Obtain the 10 point DFT of the sequence $x(n) = \delta(n) + 2\delta(n - 5)$. [5+5]

5.a) Find the IDFT of the sequence

$X(K) = \{20, -5.828-j2.414, 0, -0.712-j0.414, 0, -0.172+j0.414, 0, -5.828+j2.414\}$ using DIT-FFT algorithm.

b) Using FFT and IFFT, determine the output of system if input $x(n) = \{2, 2, 4\}$ and impulse response $h(n) = \{1, 1\}$. [5+5]

6.a) Design a digital low pass filter using Chebyshev filter that meets the following Specifications: Passband magnitude characteristics that is constant to within 1dB for frequencies below $\omega = 0.2\pi$ and stopband attenuation of at least 15dB for frequencies between $\omega = 0.3\pi$ and π . Use bilinear transformation.

b) An analog filter has the following system function. Convert this filter into a digital filter by using the impulse invariant technique: [5+5]

$$H(s) = \frac{1}{(s+0.1)^2 + 9}$$

7.a) Using a bilinear transformation, design a Butterworth filter which satisfies the following conditions:

$$0.8 \leq |H(e^{j\omega})| \leq 1 \quad 0 \leq \omega \leq 0.2\pi$$

$$|H(e^{j\omega})| \leq 0.2 \quad 0.6\pi \leq \omega \leq \pi$$

b) Determine $H(z)$ using impulse invariance method for the following system function: [5+5]

$$H_a(s) = \frac{1}{(s+0.5)(s^2+0.5s+2)}$$

8.a) The desired frequency response of a low pass filter is given

$$H_d(e^{j\omega}) = \begin{cases} e^{-j\omega} & -\frac{3\pi}{4} \leq \omega \leq \frac{3\pi}{4} \\ 0 & \frac{3\pi}{4} \leq |\omega| \leq \pi \end{cases}$$

Find $H(e^{j\omega})$ for $M=7$ using a rectangular window

b) Explain the type II frequency sampling method of designing an FIR digital filter. [5+5]

OR

9.a) Design a band pass filter which approximates the ideal filter with cutoff-frequencies at 0.2rad/sec and 0.3rad/sec. The filter order is $M=7$. Use the Hanning window function [5+5]

b) Design an ideal band pass filter with a frequency response.

$$H_d(e^{j\omega}) = \begin{cases} 1 & \text{for } \frac{\pi}{4} \leq |\omega| \leq \frac{3\pi}{4} \\ 0 & \text{otherwise} \end{cases}$$